



SolarEdge Power Optimizer

Module Add-On for Commercial Installations

P600 / P700 / P800p / P800s



POWER OPTIMIZER

PV power optimization at the module-level

The most cost effective solution for commercial and large field installations

- Specifically designed to work with SolarEdge inverters
- Up to 25% more energy
- Superior efficiency (99.5%)
- Balance of System cost reduction; 50% less cables, fuses and combiner boxes, over 2x longer string lengths possible
- Fast installation with a single bolt
- Advanced maintenance with module-level monitoring
- Module-level voltage shutdown for installer and firefighter safety
- Use with two PV modules connected in series or in parallel



SolarEdge Power Optimizer Module Add-On For Commercial Installations P600 / P700 / P800p / P800s

| Optimizer model (typical module compatibility) | P600 (for 2 x 60-cell PV modules) | P700 (for 2 x 72-cell PV modules) | P800p (for parallel connection of 2x 96-cell 5" PV modules) | P800s (for series connection of 2x high power or bi-facial modules) | |
|---|--|--|---|--|---------|
| INPUT | | | | | |
| Rated Input DC Power ⁽¹⁾ | 600 | 700 | 800 | | W |
| Absolute Maximum Input Voltage (Voc at lowest temperature) | 96 | 125 | 83 | 120 | Vdc |
| MPPT Operating Range | 12.5 - 80 | 12.5 - 105 | 12.5 - 83 | 12.5 - 105 | Vdc |
| Maximum Short Circuit Current (Isc) | 10.1 | | 14 | 12.5 | Adc |
| Maximum Efficiency | | | | 99.5 | % |
| Weighted Efficiency | | | | 98.6 | % |
| Overtoltage Category | | | | II | |
| OUTPUT DURING OPERATION (POWER OPTIMIZER CONNECTED TO OPERATING SOLAREEDGE INVERTER) | | | | | |
| Maximum Output Current | 15 | | 18 | | Adc |
| Maximum Output Voltage | | | | 85 | Vdc |
| OUTPUT DURING STANDBY (POWER OPTIMIZER DISCONNECTED FROM SOLAREEDGE INVERTER OR SOLAREEDGE INVERTER OFF) | | | | | |
| Safety Output Voltage per Power Optimizer | | | | 1 ± 0.1 | Vdc |
| STANDARD COMPLIANCE | | | | | |
| EMC | | | | FCC Part15 Class B, IEC61000-6-2, IEC61000-6-3 | |
| Safety | | | | IEC62109-1 (class II safety) | |
| RoHS | | | | Yes | |
| Fire Safety | | | | VDE-AR-E 2100-712:2013-05 | |
| INSTALLATION SPECIFICATIONS | | | | | |
| Compatible SolarEdge Inverters | Three phase inverters SE15K & larger | | Three phase inverters SE16K & larger | | |
| Maximum Allowed System Voltage | | | | 1000 | Vdc |
| Dimensions (W x L x H) | 128 x 152 x 43 / 5 x 5.97 x 1.69 | 128 x 152 x 50 / 5 x 5.97 x 1.93 | 128 x 158 x 59 / 5 x 6.22 x 2.32 | 128 x 152 x 59 / 5 x 5.97 x 2.32 | mm / in |
| Weight (including cables) | 834 / 1.8 | 933 / 2.1 | 1019 / 2.2 | 1064 / 2.3 | gr / lb |
| Input Connector ⁽²⁾ | MC4 | | MC4 Dual Input ⁽⁶⁾ | | MC4 |
| Output Connector | | | MC4 | | |
| Output Wire Length | 1.2 / 3.9 (portrait orientation) or 1.8 / 5.9 (landscape orientation) | 1.2 / 3.9 (portrait orientation) or 2.1 / 6.9 (landscape orientation) | 1.2 / 3.9 (portrait orientation) or 1.8 / 5.9 (landscape orientation) ⁽⁴⁾ | 1.2 / 3.9 (portrait orientation) or 2.1 / 6.9 (landscape orientation) | m / ft |
| Operating Temperature Range ⁽³⁾ | | | | -40 - +85 / -40 - +185 | °C / °F |
| Protection Rating | | | | IP68 / NEMA6P | |
| Relative Humidity | | | | 0 - 100 | % |

⁽¹⁾ Rated STC power of the module. Module of up to +5% power tolerance allowed.

⁽²⁾ For other connector types please contact SolarEdge.

⁽³⁾ For ambient temperature above +70°C / +158°F power de-rating is applied. Refer to Power Optimizers Temperature De-Rating Application Note for more details.

| PV SYSTEM DESIGN USING A SOLAREEDGE INVERTER ⁽⁵⁾⁽⁶⁾ | | THREE PHASE SE15K AND LARGER | THREE PHASE SE16K AND LARGER | THREE PHASE FOR MV GRID | |
|--|------------------|------------------------------|------------------------------|----------------------------|---|
| Compatible Power Optimizers | | P600 | P600, P700 P800 | P600, P700 P800 | |
| Minimum String Length | Power Optimizers | 13 | 12 | 13 | |
| | PV Modules | 26 | 24 | 26 | |
| Maximum String Length | Power Optimizers | | 30 | | |
| | PV Modules | | 60 | | |
| Maximum Power per String | | 11250 ⁽⁷⁾ | 13500 | 12750 ⁽⁸⁾ 15300 | W |
| Parallel Strings of Different Lengths or Orientations | | | Yes | | |

⁽⁵⁾ P600 and P700 can be mixed in one string. It is not allowed to mix P600/P700/P800 with P300/P370/P500/P404/P405/P505 in one string.

⁽⁶⁾ In a case of odd number of PV modules in one string it is allowed to install one P600/P700/P800 power optimizer connected to one PV module. When connecting a single module to the P800p seal the unused input connectors with the supplied pair of seals.

⁽⁷⁾ For SE27.6K, SE50K, SE55K, SE82.8K: It is allowed to install up to 13,500W per string when 3 strings are connected to the inverter and when the maximum power difference between the strings is up to 2,000W; inverter max DC power: 37,250W.

⁽⁸⁾ For inverters for MV grid: It is allowed to install up to 15,000W per string when 3 strings are connected to the inverter and when the maximum power difference between the strings is up to 2,000W; inverter max DC power: 45,000W.

